

# INTELLIGENT OFFICE

## Motion Sensor

Detects motion in zones

Office space isn't cheap. Streamline the use of space in your building to avoid having unused zones. Motion Sensor detects motion, for example when people are entering a room, indicating that it is being used. It instantly connects with our platform, giving you a visual view of used/not used zones\* and insights for making more efficient decisions.

### No more guesswork

- Get information if a room is used when pre-booked\*
- Utilization Reporting
- No-show Reporting\*
- Trigger meeting events\*

\*Requires ROL Booking System



## TECHNICAL INFORMATION



### Weight

70 g  
2.5 oz



### Wifi

Wi-Fi/WLAN  
IEEE® 802.11 b/g/n (2.4 GHz)



### Operating Temperature

10°C - 25°C  
50°F - 77°F



### Dimensions

84 x 28 x 44 mm  
3.3 x 1.1 x 1.7 inch



### Network security

IEEE 802.11 WEP, WPA, WPA2 Security  
(not 802.11x WPA-Enterprise)



### Color and material

White, ABS



### Connections

ROL Programming port,  
Mini-USB for charging



### FCC ID

2ADHKATWINC1500



### Included

Battery included (mounted inside)



### Detection Capabilities

84°x94° degrees  
Max distance 5 m / 16.4 feet  
(depending on mounting)



### Battery

Rechargeable Lithium-Ion battery  
Capacity 3.8V 1400 mAh  
Charging time 12 hours



### Add-ons

Mini-USB power charger  
Wall mount kit  
Mini-USB cable

Also detects environmental  
temperature around the sensor

## PLATFORM

---

### Easy Setup

- ✓ Can be pre-configured with Wifi-profiles for easy deployment
- ✓ Up and running within minutes
- ✓ Wall mount kit available if mounting is needed on non-magnetic surfaces

### Simple Mounting

- ✓ Magnets to mount on existing metal surfaces like ceiling rails and desk crossbars etc

### Rechargeable battery

- ✓ 1 year battery life under normal operation
- ✓ Light indication for low power
- ✓ Charging power with standard mini-USB cable

## DIMENSIONS

---

