

INTELLIGENT OFFICE

Presence Sensor

Monitors presence per desk and per seat

Identify unused desks and rooms with our Presence Sensor. Presence Sensor can monitor the number of participants in a room and present utilization rate per room and per seat. It can also detect how much a specific desk is being used to help you streamline the use of space in the office. The sensor detects presence by detecting body temperature.

No more guesswork

- Identify and understand your spaces
- Reduce waste of resources
- Get utilization rate on number of seats in conference room
- Get utilization rate per desk
- Identify free space and desks with Floorplan*

*Requires ROL Booking System



TECHNICAL INFORMATION

Weight

70 g
2.5 oz

Wifi

Wi-Fi/WLAN
IEEE® 802.11 b/g/n (2.4 GHz)

Operating Temperature

10°C - 25°C
50°F - 77°F

Dimensions

84 x 28 x 44 mm
3.3 x 1.1 x 1.7 inch

Network security

IEEE 802.11 WEP, WPA, WPA2 Security
(not 802.11x WPA-Enterprise)

Color and material

White, ABS

Connections

ROL Programming port,
Mini-USB for charging

FCC ID

2ADHKATWINC1500

Included

Battery included (mounted inside)

Detection Capabilities

60°. Max distance 1 m / 3.3 feet

Also detects environmental
temperature around the sensor

Battery

Rechargeable Lithium-Ion battery
Capacity 3.8V 1400 mAh
Charging time 12 hours

Add-ons

Mini-USB power charger
Wall mount kit
Mini-USB cable

PLATFORM

Easy Setup

- ✓ Can be pre-configured with Wifi-profiles for easy deployment
- ✓ Up and running within minutes
- ✓ Wall mount kit available if mounting is needed on non-magnetic surfaces

Simple Mounting

- ✓ Magnets to mount on existing metal surfaces like ceiling rails and desk crossbars etc

Rechargeable battery

- ✓ 1 year battery life under normal operation
- ✓ Light indication for low power
- ✓ Charging power with standard mini-USB cable

DIMENSIONS

